

APRSlink Commands

update 2016-02-16 1700z

WLNK-1	COMMENT text part of the APRS station to be stated for automatic info message from the server that Winlink messages are available ! Plus it is the CALLSIGN to forward the available queries to.
H or ?	Return brief Help. Help is also returned whenever APRSlink does not understand a command. Use "?" followed by a command letter for detailed help for that command. Example: "?L" for help with the List command.
L	Return a List of pending messages (a maximum of 5 are returned). The List command queries the Winlink e-mail server and builds a list of up to 5 recent messages. Other commands operate on this list of messages using the message number (#).
R#	Read message number # (# is one of the numbered messages returned via the List command). Example: "R2"
Y#	reply to message. Reply to message number # (# is one of the numbered messages returned via the List command). Example: "Y2"
SP	This simplifies the sending of messages from APRS devices considerably. Here's the format: SP <email address – or- callsign –or- alias> <subject> Then, anything you send to WLNK-1 other than /EX or the (P)layback command makes up the body of your message. If you mess up and need to start over, just issue a new SP command. Example (all sent to WLNK-1): SP sam@iam.com Header Test Message Some text for the body of the message. Some more text for the message. /EX Each line is a separate APRS message, but the need for entering specific commands for each line/message has been removed. You type and send as much text as necessary and then send /EX as a separate APRS message to complete your email.
/EX	Complete and send the composed message. You should receive a confirmation message.
P	Playback message. Play back message lines for the message being written.
SMS	Send short message (one line). Syntax: SMS <email address, callsign, or alias> <message> Example: SMS sam@iam.com A short message to Sam
A AL	Create/update an alias for an e-mail address. Example: A sam=sammy.miller@somelongdomainname.net Then use "SP sam" instead of "W sam@somelongdomainname.net" To delete an alias omit the part after the equal sign. "A sam=" will delete the sam alias. To get a list of all your aliases send "AL"
F#	Forward message number # to address or callsign following F# (# is 1 to 5) (# is one of the numbered messages returned via the List command). Example: "F2 youraddr@home.net"
K#	Kill (mark as deleted) message number # (# is one of the numbered messages returned via the List command). Example: "K3"
G#	Return information about closest active RMS Packet Gateway. # is a number indicating how many "close" stations are returned. The default (no #) is 1.
I	Return Information about APRSlink

All informations provided by WINLINK.ORG

compiled by SA7SKY